



Tanúsítvány beállítása az
IWS-hez

PRIMON 6.0

NYOMTATÁS-KÖVETŐ ÉS VEZÉRLŐ
RENDSZER

TANÚSÍTVÁNY BEÁLLÍTÁSA AZ IWS-HEZ

Az MFP weboldalára jelentkezzünk be Adminisztrátori módba. Majd lépünk be a Security menübe.

 **KONICA MINOLTA**

 **Page Scope Web Connection**

Model Name: bizhub 227

 Administrator

Logout 

 Ready to Scan

 Ready to Print





MaintenanceSystem Settings**Security**User Auth/Account TrackNetworkBox

Print SettingStore AddressWizardCustomizeTo Main Menu

▼ PKI Settings

- ▶ Device Certificate Setting
- ▶ SSL Setting
- ▶ Protocol Setting
- ▶ External Certificate Setting
- ▶ Certificate Verification Settings
- ▶ Address Reference Setting
- ▶ Restrict User Access
- ▶ Auto Logout
- ▶ Administrator Password Setting
- ▶ TX Operation Log Setting
- ▶ Quick Security Setting

Device Certificate List

New Registration

Default	Issuer	Subject	Validity Period	Detail	Setting
☒	KM9BE1F3.primon2....	KM9BE1F3.primon2....	01/09/2025	Detail	Setting

OKCancel


A Security menüpontban, ha van tanúsítvány, töröljük, majd adjunk hozzá egy újat az alábbi paraméterekkel. Az A4-es gépeken kötelező minden lehetőséget kitölteni, ezért tegyünk így az A3-as gépeknél is.

**KONICA MINOLTA**

 **Web Connection**

Model Name: bizhub 227

 Administrator

 Logout 

 Ready to Scan

 Ready to Print





Maintenance

System Settings

Security

User Auth/Account Track

Network

Box

Print Setting

Store Address

Wizard

Customize

 To Main Menu

▼ PKI Settings

► Device Certificate Setting

► SSL Setting

► Protocol Setting

► External Certificate Setting

► Certificate Verification Settings

► Address Reference Setting

► Restrict User Access

► Auto Logout

► Administrator Password Setting

► TX Operation Log Setting

► Quick Security Setting

Create and install a self-signed Certificate.

Common Name

192.168.132.43

Organization

Organizational Unit

Locality

State/Province

Country

Admin. E-mail Address

Validity Start Date

Validity Period

Day(s)(1-3650)

Encryption Key Type

OK

Cancel

Ezután lépünk át az SSL Setting menüpontba és kapcsoljuk be a Mode using SSL/TLS pontot az alábbiak szerint Admin. Mode and User Mode.

The screenshot displays the Konica Minolta Web Connection interface. At the top, the header includes the Konica Minolta logo, the text 'Web Connection', and the model name 'bizhub 227'. The user is logged in as 'Administrator' with a 'Logout' button and a help icon. Below the header, there are several menu tabs: 'Maintenance', 'System Settings', 'Security' (highlighted), 'User Auth/Account Track', 'Network', and 'Box'. Under the 'Security' tab, there are sub-tabs: 'Print Setting', 'Store Address', 'Wizard', 'Customize', and 'To Main Menu'. The 'SSL Setting' sub-tab is selected, showing a list of settings on the left and the configuration details on the right. The settings on the left include 'PKI Settings', 'Device Certificate Setting', 'SSL Setting' (highlighted), 'Protocol Setting', 'External Certificate Setting', 'Certificate Verification Settings', 'Address Reference Setting', 'Restrict User Access', 'Auto Logout', 'Administrator Password Setting', 'TX Operation Log Setting', and 'Quick Security Setting'. The 'SSL Setting' configuration details on the right include: 'Mode using SSL/TLS' set to 'Admin. Mode and User Mode', 'Encryption Strength' set to 'AES-256, 3DES-168, RC4-128', and 'SSL/TLS Version Setting' with checkboxes for 'SSLv3', 'TLSv1.0', 'TLSv1.1', and 'TLSv1.2', all of which are checked. At the bottom right, there are 'OK' and 'Cancel' buttons.

KONICA MINOLTA
Web Connection
Model Name: bizhub 227

Administrator Logout ?

Ready to Scan
Ready to Print

Maintenance System Settings **Security** User Auth/Account Track Network Box

Print Setting Store Address Wizard Customize To Main Menu

▼ PKI Settings

- ▶ Device Certificate Setting
- ▶ **SSL Setting**
- ▶ Protocol Setting
- ▶ External Certificate Setting
- ▶ Certificate Verification Settings
- ▶ Address Reference Setting
- ▶ Restrict User Access
- ▶ Auto Logout
- ▶ Administrator Password Setting
- ▶ TX Operation Log Setting
- ▶ Quick Security Setting

SSL Setting

Mode using SSL/TLS Admin. Mode and User Mode ▼

Encryption Strength AES-256, 3DES-168, RC4-128 ▼

SSL/TLS Version Setting

- ☒ SSLv3
- ☒ TLSv1.0
- ☒ TLSv1.1
- ☒ TLSv1.2

OK Cancel

A beállítás végeztével lépünk ki.



COLORSPECTRUM KFT

1131 Budapest, Dolmány u. 26.

Tel.: +36 1 303-9009

Fax: +36 1 210-1482

E-mail: info@printmonitoring.com

www.printmonitoring.com